

RADIOODTWARZACZ JVC KD-R771BT



CENA: **508,00** PLN

CZAS WYSYŁKI: 3 DNI

PRODUCENT: JVC

NUMER KATALOGOWY: KD-R771BT



OPIS PRZEDMIOTU

RADIOODTWARZACZ USB /MP3/ BLUETOOTH/CD JVC KD-R771BT

POLSKA GWARANCJA **24 MIESIĘCE**

RADIOODTWARZACZ CD Z PORTEM USB, WEJSCIEM AUX ORAZ
TECHNOLOGIA BLUETOOTH®.





- MOS-FET 50 W X 4
- ODTWARZANIE PLIKÓW: CD: MP3 / WMA
- USB: WAV / MP3 / WMA / FLAC
- TRYB ODTWARZANIA PLIKÓW AUDIO Z URZĄDZEŃ Z SYSTEMEM ANDROID PRZESZ USB
- TECHNOLOGIA BLUETOOTH® (JEDNOCZESNE PAROWANIE DWÓCH TELEFONÓW/)
- WEJŚCIE USB NA PRZEDNIM PANELU (1.5A)
- WEJŚCIE AUX NA PRZEDNIM PANELU
- TUNER CYFROWY Z RDS
- RADIO TIMER (USTAWIENIA DZIENNE/ TYGODNIOWE)
- 13-PASMOWY KOREKTOR PARAMETRYCZNY IEQ8 USTAWIEŃ EQUALIZERA
- 4V POZIOM WYJŚCIA LINIOWEGO I WYJŚCIE SUBWOOFERA
- DIGITAL TRACK EXPANDER
- REGULACJA JASNOŚCI NIEZALEŻNIE DLA PRZYCISKÓW I WYŚWIETLACZA
- MOŻLIWOŚĆ WSPÓŁPRACY Z FABRYCZNYM STEROWANIEM AUDIO
- TECHNOLOGIA POPRAWY DŹWIĘKU K2
- ZDEJMOWANY PANEL PRZEDNI

Media Playback	
MP3/WMA Compatible with ID3 Tag/WMA Tag	CD / USB
WAV Compatible with Tag	USB
FLAC Compatible with Tag	USB
CD Player	
CD-R/RW Compatible	Yes
CD Text	Yes
Random/Repeat Play	Yes
Frequency Response	20 - 20,000Hz (+/-1dB)
Dynamic Range	90dB
Signal-to-Noise Ratio	105dB (1kHz)
Channel Separation	85dB
Wow & Flutter	Below measureable limit
Bluetooth Control	
Bluetooth Control [1]	Yes (Built-in, Wired-Mic included)
2 Phones Full-Time Connection	Yes
Hands Free Call (HFP)	Yes (HFP 1.6 wideband speech)
Audio Streaming & Control (A2DP, AVRCP)	Yes
Voice Recognition Dialing (compatible mobile phone required)	Yes
Siri Eyes Free Mode for iPod/iPhone	Yes
Phone Book Access Profile (PBAP)	Yes
iPhone & Android Automatic Pairing	Yes

Android Control	
Android Music Playback (AUDIO MODE and AUTO MODE)	Yes (AUDIO MODE & AUTO MODE) [3]
Pandora Control [2]	Yes (via Bluetooth®)
Battery Charge	Yes (USB: 1.5A Max.)
iPod/iPhone Control	
iPod/iPhone Music Playback	Yes
Random/Repeat Play	Yes
Text	Yes
Battery Charge	Yes (USB: 1.5A Max.)
Pandora Control [2]	Yes (USB)
USB	
Position	Front
Random/Repeat Play	Yes
USB Power Supply	Yes (1.5A)
USB Mass Storage Class (for music files)	Yes
Drive Change Mode for Mass Storage Class	Yes
Tuner	
Radio Data System (RDS)	Yes (with Radio Text Plus)
Digital Processing Tuner	Yes
Preset Stations	18FM + 6AM + 12SW
Strong Station Memory (for FM)	Yes
Radio Timer	Yes (Once/Daily/Weekly)
Tuner Preset Memory (for power disconnection)	Yes
FM	
Frequency Range	87.5 - 108.0MHz
Usable Sensitivity	8.2dBf (0.71uV/75 ohms)
Quieting Sensitivity (46dB)	17.2dBf (2.0uV/75 ohms)
Stereo Separation	40dB
AM	
Frequency Range	(MW) 531 - 1,611kHz (9kHz), (SW1) 2,940 kHz to 7,735 kHz (5 kHz step), (SW2) 9,500 kHz to 10,135 kHz (5 kHz step) / 11,580 kHz to 18,135 kHz (5 kHz step)
Sensitivity	(MW) 28.2uV, (SW) 32uV
Audio	
Maximum Power Output	50W x 4 / 50W x 2 +Subwoofer (4 ohms) 50W x 1
Typical Power Output	22W x 4 (Full Bandwidth Power, at less than 1% THD)
MOS-FET Amplifier	Yes
Sub woofer Direct Connection (Mono Lch)	Yes
Audio DAC	Yes
EQ	
13-Band Graphic EQ	Yes
Easy EQ Setting	Yes
Preset EQ	Yes (8-preset)
Source Link EQ	Yes
Loudness Control	Yes (Off/Low/High)
High-Pass Filter/Low-Pass Filter	Yes/Yes
K2 Technology	Yes
Space Enhancement	Yes
Sound Response	Yes
Sound Lift	Yes
Volume Link EQ	Yes
Load Impedance	4 ohms (4 - 8 ohms)
Pre-Output Level	4.0V
Line Output Impedance	Less than 600 ohms

Subwoofer Output Level	4.0V
Inputs and Outputs	
AUX Input	1 (Front)
Line Output Terminals (Pair)	3 Pairs (Front + Rear + Subwoofer)
Subwoofer Output with Level/Frequency Control	Yes (Level -50 - +10)
Display	
Variable Colour	Yes (3-Zone)
Illumination Colour	Variable (3-Zone)
Spanish Text Display Compatible	Yes
Auto Dimmer	Yes
Brightness Control	Yes
General	
Detachable Face Panel	Yes
Carrying Case	Yes
Wireless Remote Control	Yes
Steering Remote Control Ready	Yes
Dimensions (W x H x D)	
Installation Size	182 x 53 x 158mm
Weight	1.1kg